

## Demo for BIO 656-Turbo:

Built in Oven, GL 656 Turbo, mein front panel par, Left hand side par ek function selector, extreme Right side par thermostat (temperature set karne ke liye) aur center mein digital timer hai.

Function selector se aap 8 functions select kar sakte hain.

Top position: Off mode hai.

Clockwise rotate karte hue:

1. Light
2. Defrost
3. Upper + Lower element
4. Turbo fan + circular back element
5. Upper half element
6. Upper complete element
7. Upper element with fan
8. Lower element with fan

Thermostat se aap temperature 25-250 deg celcius tak select kar sakte hain.

Oven ON karte he digital display 0:00, blinking mode mein show karega.

Koi bhi 2 button ek saath press karein, immediately + or – button press karte hue, 24H clock mein real clock time set karein.

Manual use karne ke liye, 'hand' button press karein, thermostat se temperature set karein aur function selector se cook mode set karein.

Manual mode mein timer fix karne ke liye, 'hand' button press karein aur time fix karne ke liye 'bell' button press karein. Time +/- button se set karein.

Time complete hone par, beep ki awaz aayegi, but oven band nahi hoga. Oven aapko manually band karna hoga.

'Auto' mode par use karne ke liye, cooking time button press karein aur +/- button se time set karein.

Time pura hone par oven beep ke saath Off ho jayega.

Auto mode par aap end time bhi set kar sakte hain.

Stop button press karein aur + button se real clock time set karein jab aapko cooking khatam karni hai.

Real clock mein woh time aate he, oven beep ke saath off ho jayega.

GL 656 Turbo mein aap apni absence mein bhi usse operate kar sakte hain.

Pehle stop button se end time set karein jab aapko oven Off karna hai. Phir cooking time button press karein aur '-' button se cook time fix karein jitni der ke liye aapko oven On karna hai.

End time se cook time pehle, oven automatically ON ho jayega aur End time par aate hi Off ho jayega.